

AUSTRALIA

15094/85
APPLICATION ACCEPTED FOR AMENDMENTS
ALLOWED 20-7-85

COMMONWEALTH OF AUSTRALIA
PATENTS ACT 1952

SPRUSON & FERGUSON

CONVENTION APPLICATION FOR A STANDARD PATENT

We NEC Corporation of 33-1, Shiba 5-chome, Minato-ku,
Tokyo, Japan hereby apply for the grant of a standard patent for
an invention entitled:

"PAGER WITH DISPLAY"

which is described in the accompanying complete specification.

DETAILS OF BASIC APPLICATION

Number of Basic Application:-
P59-150421

FEE STAMP TO VALUE OF
180
1 ATTACHED
MAIL OFFICER

Name of Convention Country in which Basic
Application was filed:-
Japan

Date of Basic application:-
18 July 1984

LODGED AT SUB-OFFICE
16 JUL 1985
Sydney

Our address for service is:-

C/- Spruson & Ferguson
Patent Attorneys
Level 33 St Martins Tower
31 Market Street
Sydney New South Wales Australia

DATED this FIFTEENTH day of JULY 1985

NEC Corporation

By:

[Signature]
Registered Patent Attorney.

TO: THE COMMISSIONER OF PATENTS

Spruson & Ferguson

COMMONWEALTH OF AUSTRALIA

THE PATENTS ACT 1952

DECLARATION IN SUPPORT OF A
CONVENTION APPLICATION FOR A PATENT

In support of the Convention Application made for a
patent for an invention entitled:

Title of Invention

"PAGER WITH DISPLAY"

Full name(s) and
address(es) of
Declarant(s)

I/We Susumu Uchihara

of c/o NEC Corporation of 33-1, Shiba 5-chome,
Minato-ku, Tokyo, Japan

do solemnly and sincerely declare as follows:-

Full name(s) of
Applicant(s)

1. I am/We are the applicant(s) for the patent-

(or, in the case of an application by a body corporate)

1. I am/We are authorised by

NEC Corporation

the applicant(s) for the patent to make this declaration on
its/their behalf.

2. The basic application(s) as defined by Section 141 of the
Act was/were made

Basic Country(ies)

in Japan.

Priority Date(s)

on the 18th July, 1984

Basic Applicant(s)

by NEC Corporation

Full name(s) and
address(es) of
inventor(s)

3. I am/We are the actual inventor(s) of the invention referred
to in the basic application(s)-

(or where a person other than the inventor is the applicant)

3. Takashi OYAGI and Kazuyuki TSUNODA

both

of c/o NEC Corporation of 33-1, Shiba 5-chome,
Minato-ku, Tokyo, Japan

are the actual inventor(s) of the invention and the facts upon
which the applicant(s) is/are entitled to make the application are
as follows:

Set out how Applicant(s)
derive title from actual
inventor(s) e.g. The
Applicant(s) is/are the
assignee(s) of the
invention from the
inventor(s)

The said applicant is the assignee of the actual inventors.

4. The basic application(s) referred to in paragraph 2 of this
Declaration was/were the first application(s) made in a Convention
country in respect of the invention(s) the subject of the application.

Declared at Tokyo, Japan this 30th day of July, 1985
NEC Corporation

To: The Commissioner of Patents

Susumu Uchihara
Signature of Declarant(s)
Susumu Uchihara

Must have in
English letters
and be in English
and be in English

(12) PATENT ABRIDGMENT (11) Document No. AU-B-45044/85
(19) AUSTRALIAN PATENT OFFICE (10) Acceptance No. 579534

(Modified Examination)

(54) Title
PAGER WITH DISPLAY

(51)* International Patent Classification(s)
G08B 007/06

(21) Application No.: 45044/85 (22) Application Date: 16.07.85

(30) Priority Data

(31) Number (32) Date (33) Country
59-150421 18.07.84 JP JAPAN

(43) Publication Date: 23.01.86

(44) Publication Date of Accepted Application: 24.11.88

(71) Applicant(s)
NEC CORPORATION

(72) Inventor(s)
TAKASHI OYAGI; KAZUYUKI TSUNODA

(74) Attorney or Agent
SPRUSON & FERGUSON

(56) Prior Art Documents
33489/84 570382 G08B 7/06
US 3849979
US 3937004

(57) Claim

1. A display pager, comprising:

data processing means for processing a received signal to generate an information signal, and for generating a control signal;

display means for optically displaying on the display alphanumeric characters corresponding to the information signal output by said data processing means;

light sensor means for sensing an external luminance level in the vicinity of said display means and for applying a first sense signal to the data processing means when said luminance level is lower than a first predetermined value, and for applying a second sense signal to the data processing means when said luminance level is above a second predetermined value which is higher than said first predetermined value; and illuminating means for illuminating the display means in response to the control signal output from the data processing means, said illuminating means including a lamp;

the data processing means generating said control signal in response to said first sense signal during the operation of the display of the display means and controlling said illuminating means to turn off said lamp in

(11) AU-B-45044/85
(10) 579534

-2-

response to said second sense signal.

A pager as claimed in claim 1, wherein said data processing means turns off said lamp when the operation of the display of the display means is terminated.

FORM 10

SPRUSON & FERGUSON

COMMONWEALTH OF AUSTRALIA
PATENTS ACT 1952

COMPLETE SPECIFICATION

(ORIGINAL)
FOR OFFICE USE:

Class Int. Class

45044/25.

This document contains the
first claims made under
Section 49 and is correct for
printing.

Complete Specification Lodged:

Accepted:

Published:

Priority:

Related Art:

Name of Applicant: NEC Corporation

Address of Applicant: 33-1, Shiba 5-chome, Minato-ku, Tokyo, Japan

Actual Inventor(s): TAKASHI OYAGI and KAZUYUKI TSUNODA

Address for Service: Spruson & Ferguson, Patent Attorneys,
Level 33 St Martins Tower, 31 Market
Street, Sydney,
New South Wales, 2000, Australia

Complete Specification for the invention entitled:

"PAGER WITH DISPLAY"

The following statement is a full description of this invention,
including the best method of performing it known to us.

PAGER WITH DISPLAY
BACKGROUND OF THE INVENTION

The present invention relates to a pager with a display and, more particularly, to a display pager of the type using liquid crystal or like display elements which are not themselves radiant, and which is capable of automatically illuminating the display as the external luminance becomes low.

Some modern pagers are capable of displaying data in numerals and messages to convey such information to the user. The prerequisite for this type of pager is that it be small in size and portable and, to meet this need, non-radiant liquid crystal elements which consume a minimum of power are widely used. Because these display elements are non-radiant as mentioned, such a pager is provided with a lamp for illumination and a switch associated with the lamp.

One approach to a smaller-size configuration is to replace the switch with a light-sensing photo-sensing phototransistor, as disclosed in Japanese Patent Application Ser. No. 58-178683 corresponding to U.S. patent application Ser. No. 654,082, now U.S. Pat. No. 4,644,350, 2-17-87, EPC Patent Application No. 84 111 419.2, Canadian Patent Application No. 463,961. An example of the phototransistor scheme is shown in FIG. 1.

In the prior art pager shown in FIG. 1, phototransistor 10a is sensitive to external luminance and, when it is low, turns on a lamp 10b. When the lamp 10b is turned on, light issuing from the lamp 10b is diffused inside a diffuser plate 12 and transmitted sequentially through liquid crystal 14 and an acrylic plate 16 as indicated by arrows, thereby allowing displayed data to be read by the user. A partition plate 18 serves to intercept a part of the light from the lamp 10b which is directed toward the phototransistor 10a.

However, although the partition plate 18 successfully prevents the light from the lamp 10b from becoming directly incident to the phototransistor 10a, it fails to intercept the light reflected by the acrylic plate 16 as well as externally derived light. Therefore, when the external luminance is dim, the display cannot function in a positive manner. Specifically, when the luminance level is near the threshold level which will permit photosensor 10a to turn on the lamp, the output signal of the photosensor is susceptible to even insignificant changes in the ambient conditions and leakage of light issuing from the lamp 10b (as is indicated by phantom lines in FIG. 1) can cause the lamp 10b to repeatedly turn on and



off at short intervals, rendering the displayed information difficult to see.

SUMMARY OF THE INVENTION

It is therefore an object of the present invention to provide a display pager which eliminates the above-discussed drawback and allows displayed information to be read with ease even in a dim ambient.

It is another object of the present invention to provide a generally improved display pager.

The pager of the present invention comprises a data processing
10 circuit for processing a received signal to generate an information signal
to be displayed and a control signal, a display circuit for optically
displaying on the display the information signal which is outputted from
the data processing circuit, a light sensor for sensing the external
luminance level around the display circuit and for applying a first sense
signal to the data processing circuit when the level is lower than a first
predetermined value, and an illuminating circuit for illuminating the
display ^{response} ~~response~~ to the control signal output from the data processing
circuit, the illuminating circuit including a lamp.

The data processing circuit is constructed to generate the control
20 signal when the external luminance sensed by the light sensor is lower than
the first predetermined value and the display of the display circuit is
maintained.

In accordance with the present invention, a pager has a display
implemented with, for example, a liquid crystal and senses the external
luminance so that the display can be automatically illuminated when the
luminance has decreased.

The above and other objects, features and advantages of the present
invention will become more apparent from the following detailed description
30 taken with the accompanying drawings.

BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 is a schematic view of a prior art display pager;

FIG. 2 is a block diagram of a display pager embodying the present
invention;

FIG. 3 is a flowchart demonstrating the operation of the pager of
FIG. 2;

FIG. 4 is a diagram showing the specific construction of a light
sensing circuit;



FIGS. 5A-5D show signals appearing in the light sensing circuit and the on-off condition of a lamp;

FIG. 6 is a block diagram showing another embodiment of the present invention;

FIG. 7 is a flowchart representative of the operation of the pager of FIG. 6.

FIG. 8 is a block diagram showing another embodiment of the present invention; and

FIG. 9 is a chart representative of the operation of the pager of FIG. 8.

DESCRIPTION OF THE PREFERRED EMBODIMENTS

While the display pager of the present invention is susceptible of numerous physical embodiments, depending upon the environment and requirements of use, substantial numbers of the herein shown and described embodiments have been made, tested and used, and all have performed in an eminently satisfactory manner.

Referring to FIG. 2 of the drawings, a display pager in accordance with a preferred embodiment of the present invention is shown and generally designated by the reference numeral 20. A signal coming in through an antenna 22 is applied to a radio section 24 which is interconnected with a waveform-shaper 26. The waveform-shaper 26 is interconnected with a decoder 28 which in turn is interconnected with a read only memory (ROM) 30, a speaker 32, and a microprocessor (CPU) 34. A power source 36 has a negative terminal connected to a common potential point and to one terminal of a switch 38, and a positive terminal connected to the decoder 28 and to one input terminal of a DC-DC converter 40. The other terminal of the switch 38 is connected to the other input of the DC-DC converter 40 and to the CPU 34. An output terminal of the DC-DC converter 40 is connected to the CPU 34. Power from the power source 36 is routed via the decoder 28 to the radio section 24 and waveform-shaper 26. The output of the DC-DC converter 40 is applied to an illuminating circuit 42, a display 44 and a light sensing circuit 46 by way of the CPU 34. The CPU 34 is connected to the illuminating circuit 42, display 44 and light sensing circuit 46. The output of the light sensing circuit, or light sensor, 46 is fed to the CPU 34.

The radio section 24 amplifies and demodulates the signal coming in through the antenna 22. The wave-form-shaper 26 converts the demodulated signal to a digital signal having a format which the decoder 28 can



decode. The ROM 30 is adapted to store a call number assigned to the pager 20. The decoder 28 compares an output of the waveform-shaper 26 with the call number stored in the ROM 30 and, when they coincide with each other, applies a signal to the speaker 32 to cause it to sound, thereby alerting the user. The DC-DC converter 40 boosts the voltage applied thereto from the power source 36 so as to supply the CPU 34 with power. The switch 38 is a power switch which is manually actuated. Once the switch 38 is closed, the DC-DC converter 40 is activated to feed power to the CPU 34. When the pager 20 is called, the decoder 28 reads message data which

10 follows the call number data and applies the message data to the CPU 34. Then, the CPU 34, which includes a circuit for driving liquid crystal display segments, causes the display 44, which comprises the liquid crystal display segments, to display the message. The illuminating circuit 42 is equipped with a lamp for illuminating the display 44 and is controlled by power which is applied from the CPU 34. The light sensor 46 converts external luminance to an electrical signal which is applied to the CPU 34.

A characteristic feature of this particular embodiment is that the light sensor 46 is responsive to a first predetermined reference value associated with relatively dark ambient and a second predetermined
20 reference value associated with relatively light ambient. Specifically, the output of the light sensor 46 becomes (logical) 0 when the external luminance is lower than the first reference value (dark) and maintains the 0 level until the luminance increases beyond the second reference value (light). Conversely, the light sensor 46 produces a 1 output when the external luminance is higher than the second reference level and maintains it until the luminance decreases beyond the second reference level.

Referring to FIG. 3, the display illuminating operation of the pager 20 in accordance with the illustrative embodiment is demonstrated. The
30 operation begins when the switch 38 is closed by the user as previously mentioned. As a message is displayed on the display 44, the CPU 34 supplies power to the light sensor 46 to cause it to start measuring external luminance. (S_1 and S_2) If the measured luminance is higher
than the first reference value, the illuminating circuit 42 is not supplied with power and, therefore, the lamp is not turned on. If it is lower than the first reference value, the CPU 34 supplies power to the illuminating circuit 42 to turn on the lamp to thereby illuminate the display 44. (S_3 and S_4) In this condition, as the luminance increases beyond the second reference level, the power supply to the illuminating circuit 42 is



interrupted to turn off the lamp. (S_5 and S_6) This procedure continues until the display of the message on the display 44 is terminated. ($S_2 \sim S_7$) When the display is cancelled, the supply of power to the illuminating circuit and light sensor 46 is inhibited. (S_7 and S_8)

A specific example of the light sensor 46 is shown in FIG. 4. In this example, a phototransistor 48 has a collector connected to the CPU 34 and an emitter connected to a common potential point via a resistor 50. The emitter of the phototransistor 48 is also connected to one terminal of a resistor 52 the other terminal of which is connected to an input terminal of an inverter 54. An output terminal of the inverter 54 is connected to an input terminal of another inverter 56, an output terminal of which is connected via a resistor 58 to the input terminal of the inverter 54. The resistors 52 and 58 and the inverters 54 and 56 constitute a Schmitt circuit.

Referring to FIGS. 5A-5D, signals appearing in the light sensor 46 and the on-off condition of the lamp are shown. FIG. 5A represents the output signal or voltage of the phototransistor 48, higher voltages corresponding to higher external luminance. In FIG. 5A, the vertical axis of the signal is shown in double scale compared to the other signals for the convenience of description. When the output signal of the phototransistor 48 is binarized with an intermediate level L as a threshold, it will appear as shown in FIG. 5B. Heretofore, the output signal of the phototransistor 48 has been directly read by the CPU 34 so as to control the illuminating circuit 42, that is, the binary signal shown in FIG. 5B has been used to on-off control the lamp. Such has brought about the problem where the lamp repeatedly turns on and off at short intervals in a dim situation in which the output of the phototransistor 48 approximates the intermediate level L.

The output signal of the inverter 56 is shown in FIG. 5C. A Schmitt circuit has two different threshold voltages M_1 and M_2 ($M_1 < M_2$) and operates with hysteresis. Specifically, the output voltage of the inverter 56 becomes low when the output voltage of the phototransistor 48 has dropped below the threshold level M_1 and remains low until it rises above the threshold level M_2 . Conversely, as the output voltage of the phototransistor 48 rises beyond the threshold level M_2 , the inverter 56 produces a high voltage; the high voltage output of the inverter 56 is maintained until the phototransistor output drops beyond the threshold

level M_1 . FIG. 5D shows the on-off condition of the lamp in accordance with the illustrative embodiment, the high level representing an "on" condition. The CPU 34 turns on the lamp when the output voltage of the light sensor 46 is low when a message is being displayed on the display 44. In this particular embodiment, the lamp does not turn on and off at short intervals even in a dim ambient.

While the light sensor 46 in the above embodiment has been implemented by a Schmitt circuit, equivalent control over the illuminating circuit may be accomplished based on program control by applying the output of the phototransistor 48 to a microprocessor via an analog-to-digital converter to cause the microprocessor to compare the input signal with the two threshold levels.

Referring to FIG. 6, another embodiment of the display pager in accordance with the present invention is shown. In FIG. 6, the same or similar structural elements are designated by like reference numerals. The major difference between the pager, generally 60, of this embodiment and the previously discussed pager 20 is that in the former the CPU 34 has an output terminal for display illumination connected to the illuminating circuit 42, an output terminal for message display connected to the display 44, and an output terminal for light sensing connected to a light sensor 64 via a switch 62. The output of the light sensor 64 is coupled to the CPU 34. The switch 62 is controlled by the CPU 34.

The second illustrative embodiment is characterized in that once power is applied to the illuminating circuit 42 to turn on the lamp, the power supply to the circuit 42 is maintained until the display of the message on the display 44 is cancelled. Specifically, the switch 62 in an initial condition is closed to cause the light sensor 64 to measure external luminance. While the external luminance is low, the output voltage of the light sensor 64 remains lower than a predetermined value so that the CPU 34 supplies power to the illuminating circuit 42 and, at the same time, opens the switch 62. This interrupts the power supply to the light sensor 64, the output of which is then "0". While the light sensor output is "0", the CPU 34 applies power to the illuminating circuit 42 to turn on the lamp. The switch 62 remains open unless the message appearing on the display 44 is cancelled either automatically or manually. The light sensor 64 shown in FIG. 6 may be implemented with the circuit made up of the phototransistor 48 and resistor 50 as shown in FIG. 4.

The operation of the pager 60 is shown in a flowchart in FIG. 7.



When a message is provided on the display 44, the CPU 34 supplies power to the light sensor 64 to cause the latter to start measuring external luminance. (S_{11} and S_{12}) If the luminance has measured lower than a predetermined value, power is fed to the illuminating circuit 42 to turn on the lamp. (S_{13} and S_{14}) Once turned on, the lamp remains in that state until the message on the display 42 is cancelled. (S_{15}) If the luminance has measured higher than the predetermined value, the measurement is repeated until the end of display. (S_{12} , S_{13} and S_{16}) Upon termination of the display of the message, the supply of power to the illuminating circuit 42 and light sensor 64 is inhibited (S_{17})

10 In this particular embodiment, control is effected in a specific mode, i.e., to turn on the lamp when the light sensor output is lower than a predetermined value, in order to reduce modification of the control program. However, the illustrative embodiment can be practiced even if the control program is so modified as to maintain the lamp turned on without regard to the light sensor output after the lamp has been turned on.

In addition, since the pager 60 shown in FIG. 6 is constructed to interrupt the power supply to the light sensor 64 when the lamp has been turned on, it reduces the power which is consumed by the light sensor 64.

20 Referring to FIG. 8, another embodiment of the display pager in accordance with the present invention is shown. In FIG. 8, the same or similar structural elements are again designated by like reference numerals. The pager, generally 80, shown in FIG. 8 differs from the pager 60 of FIG. 6 in that it includes a timer 82 between the CPU 34 and the switch 62. The CPU 34 has an output terminal for display illumination connected to a trigger input terminal T of the timer 82. An output Q of the timer 82 is adapted to open and close the switch 62.

30 What characterizes this particular embodiment is that once power is supplied to the illuminating circuit 42, it is not interrupted until a predetermined period of time expires. Specifically, when power is applied to the circuit 42, it triggers the timer 82 so that the output Q of the timer 82 is maintained at the 1 level for a predetermined period of time. The "1" output of the timer 82 opens the switch 62 to cut off the power supply from the CPU 34 to the light sensor 64, resulting in a "0" light sense signal. While the light sense signal is maintained at "0", the CPU 34 applies power to the illuminating circuit 42 to turn on the lamp. Upon the lapse of the predetermined period of time, the timer 82 switches its output Q from "1" to "0" to close the switch 62, thereby reactivating the light



sensor 64.

- The operation of the pager 80 is shown in a flowchart in FIG. 9. Upon the appearance of a message on the display 44, the CPU 34 applies power to the light sensor 64 which then starts measuring external luminance. (S_{21} and S_{22}) If the luminance has measured lower than a predetermined value, power is supplied to the luminating circuit 42 and timer 82 with the result that a predetermined period of time elapses with the lamp maintained on. ($S_{23} - S_{25}$) If the luminance has measured higher than the predetermined value, the lamp if then on is turned off.
- 10 (S_{23} and S_{26}) Such a sequence of events continues until the message on the display 44 is cancelled. (S_{22} , S_{23} , $S_{26} - S_{28}$) After the message display has been cancelled, the supply of power to the illuminating circuit 42, light sensor 64 and timer 82 is inhibited. (S_{29})

In the illustrative embodiment, the output signal of the light sensor 64 is turned to "0" to control the duration of the "on" condition of the lamp. Alternatively, an arrangement may be made such that the output Q of the timer 82 is applied to the CPU 34 in order to continuously turn on the lamp while the output Q of the timer 82 is "1".

- Further, if the duration of the "on" state of the lamp is long enough
- 20 to read a message on the display 44, the lamp may be turned off without performing a further light sensing step after the lamp has been turned on.

The embodiment shown in FIG. 8 reduces the power which is consumed by the illuminating circuit 42, compared to the embodiment of FIG. 6.

Again, the embodiments shown in FIG. 6 or 8 may be implemented using program control, instead of the switch 62 and timer 82.

- In summary, it will be seen that the present invention provides the display pager which prevents a lamp from repeatedly turning on and off at short intervals in a dim situation or due to leakage of light issuing from the lamp. The pager, therefore, accomplishes an automatic illuminating
- 30 function responsive to the external luminance without degrading displayed information, thereby accurately convey a message meant for the pager user.

Various modifications will become possible for those skilled in the art after receiving the teachings of the present disclosure without departing from the scope thereof.



The claims defining the invention are as follows:

1. A display pager, comprising:

data processing means for processing a received signal to generate an information signal, and for generating a control signal;
display means for optically displaying on the display alphanumeric characters corresponding to the information signal output by said data processing means;

light sensor means for sensing an external luminance level in the vicinity of said display means and for applying a first sense signal to the data processing means when said luminance level is lower than a first predetermined value, and for applying a second sense signal to the data processing means when said luminance level is above a second predetermined value which is higher than said first predetermined value; and

illuminating means for illuminating the display means in response to the control signal output from the data processing means, said illuminating means including a lamp;

the data processing means generating said control signal in response to said first sense signal during the operation of the display of the display means and controlling said illuminating means to turn off said lamp in response to said second sense signal.

2. A pager as claimed in claim 1, wherein said data processing means turns off said lamp when the operation of the display or the display means is terminated.

3. A display pager, comprising:

data processing means for processing a received signal to generate an information signal, and for generating a control signal;
display means for optically displaying on the display alphanumeric characters corresponding to the information signal output by said data processing means;

light sensor means for sensing an external luminance level in the vicinity of said display means, said sensor means applying a first sense signal to the data processing means when said external luminance level is lower than a first predetermined value;

illuminating means for illuminating the display means in response to the control signal output from the data processing means, said illuminating means including a lamp; and

timer means triggered by said control signal for inhibiting the sensing operation of the light sensor means until the expiration of a predetermined



period of time.

the data processing means generating said control signal in response to said first sense signal.

4. A pager as claimed in claim 3, further comprising means for reactivating said light sensor means upon the expiration of said predetermined period of time.

5. A pager as claimed in claim 3, further comprising means for turning off the lamp upon the expiration of said predetermined period of time.

6. A pager, comprising:

display means for displaying a message;

means for sensing an external luminance level in the vicinity of said

display means and producing a first sense signal when said external

luminance level falls below a first predetermined level, and producing a

second sense signal when said external luminance level exceeds a second

predetermined level after said first sense signal has been produced, said

second predetermined level being higher than said first predetermined level,

means for illuminating said display means; and

control means for turning on said illuminating means in response to said

first sense signal during the display of said message on said display means

and for turning off said illuminating means in response to said second sense signal.

7. A pager as claimed in claim 6, further comprising:

means for receiving a paging signal followed by said message; and

means for detecting coincidence between a call number represented by said

paging signal and a call number assigned to said pager and for outputting

said message subsequent to said detection.

8. A pager as claimed in claim 6, wherein said illuminating means comprises a lamp.

9. A pager as claimed in claim 6, wherein said sensing means

comprises a phototransistor and a Schmitt trigger circuit connected to an

output of said phototransistor.

10. A pager as claimed in claim 6, wherein said control means comprises a microprocessor.

11. A method of controlling the illumination of a display of a pager, comprising the steps of:

displaying a message on said display;

sensing an external luminance level in the vicinity of said display;



illuminating said display when said message is being displayed on said display and the sensed external luminance level falls below a first predetermined level; and
terminating the illumination of said display when said sensed external luminance level exceeds a second predetermined level which is higher than said first predetermined level.

12. A method as in claim 11, further comprising the steps of:
receiving a paging signal followed by said message; and
comparing a call number represented by said paging signal with a call number assigned to said pager and providing said message for said display when said call numbers coincide with each other.

13. A pager, comprising:
display means for displaying a message;
means for sensing an external luminance level in the vicinity of said display means;
means for illuminating said display means when said message is being displayed on said display means and the sensed external luminance level falls below a predetermined level; and
control means for deactivating said sensing means until the display of said message on said display means is terminated.

14. A pager as claimed in claim 13, further comprising:
means for receiving a paging signal followed by said message; and
means for detecting coincidence between a call number represented by said paging signal and a call number assigned to said pager and for outputting said message subsequent to said detection.

15. A pager as claimed in claim 13, wherein said illuminating means comprises a lamp.

16. A pager as claimed in claim 13, wherein said sensing means comprises a phototransistor and a Schmitt trigger circuit connected to an output of said phototransistor.

17. A pager as claimed in claim 13, wherein said control means comprises a microprocessor.

18. A method of controlling the illumination of a display of a pager, comprising the steps of:
displaying a message on said display;
sensing an external luminance level in the vicinity of said display;
illuminating said display when said message is being displayed on said display and the sensed external luminance level falls below a predetermined



level; and
thereafter discontinuing said sensing step until the display of said message on said display means is terminated.

19. A method as claimed in claim 18, further comprising the steps of:
receiving a paging signal followed by said message; and
comparing a call number represented by said paging signal with a call number assigned to said pager and providing said message for said display when said call numbers coincide with each other.

20. A pager, comprising:
display means for displaying a message;
means for sensing an external luminance level in the vicinity of said display means;
means for illuminating said display means when said message is being displayed on said display means and the sensed external luminance level falls below a predetermined level; and
control means for deactivating said sensing means for a predetermined time after the sensed external luminance level falls below said predetermined level.

21. A pager as claimed in claim 20, further comprising:
means for receiving a paging signal followed by said message; and
means for detecting coincidence between a call number represented by said paging signal and a call number assigned to said pager and for outputting said message subsequent to said detection.

22. A pager as claimed in claim 20, wherein said illuminating means comprises a lamp.

23. A pager as claimed in claim 20, wherein said sensing means comprises a phototransistor and a Schmitt trigger circuit connected to an output of said phototransistor.

24. A pager as claimed in claim 20, wherein said control means comprises a microprocessor.

25. A method of controlling the illumination of a display of a pager, comprising the steps of:
displaying a message on said display;
sensing an external luminance level in the vicinity of said display;
illuminating said display when said message is displayed on said display and the sensed external luminance level falls below a predetermined level; and
thereafter discontinuing said sensing step until the expiration of a predetermined period of time.



26. A method as claimed in claim 25, further comprising the steps of:
receiving a paging signal followed by said message; and
comparing a call number represented by said paging signal with a call
number assigned to said pager and providing said message for said display
when said call numbers coincide with each other.

DATED this SIXTEENTH day of FEBRUARY 1988

NEC CORPORATION

Patent Attorneys for the Applicant
SPRUSON & FERGUSON



Fig. 1




Fig. 4





Fig. 5A

Fig. 5B

Fig. 5C

Fig. 5D



45 044/85

Fig. 2




Fig. 3




Fig. 6




Fig. 7




Fig. 8




Fig. 9

